

## Thiele - Small Parameter Consistency Check

MJ King  
7/03/09

### Constant Definitions

$$\text{cycle} := 2 \cdot \pi \cdot \text{rad}$$

$$\text{Hz} := \text{cycle} \cdot \text{sec}^{-1}$$

$$c := 344 \cdot \text{m} \cdot \text{sec}^{-1}$$

$$\rho := 1.205 \cdot \text{kg} \cdot \text{m}^{-3}$$

### User Input Data

#### Known Driver Thiele / Small Parameters

$$f_d := 51.5 \cdot \text{Hz}$$

$$Q_{md} := 5.391$$

$$R_e := 7.06 \cdot \text{ohm}$$

$$Q_{ed} := 0.5518$$

$$S_d := 324 \cdot \text{cm}^2$$

$$V_{ad} := 144.377 \cdot \text{liter}$$

### Calculated Parameters

#### Derived Thiele / Small Parameters

$$Q_{td} := \left( \frac{1}{Q_{ed}} + \frac{1}{Q_{md}} \right)^{-1} \quad Q_{td} = 0.501$$

$$C_{md} := V_{ad} \cdot (\rho \cdot c^2 \cdot S_d^2)^{-1} \quad C_{md} = 9.645 \times 10^{-4} \frac{\text{m}}{\text{newton}}$$

$$M_{md} := (C_{md} \cdot f_d^2)^{-1} \quad M_{md} = 9.902 \text{ gm}$$

$$Bl := \left( \frac{f_d \cdot R_e \cdot M_{md}}{Q_{ed}} \right)^{0.5} \quad Bl = 6.403 \frac{\text{newton}}{\text{amp}} \quad (1 \text{ newton/amp} = 1 \text{ Tesla-m})$$

$$\eta_o := V_{ad} \cdot (2 \cdot \pi \cdot c^3 \cdot Q_{ed} \cdot f_d^{-3})^{-1} \quad \eta_o = 3.466 \%$$

$$\text{SPL} := 112 + 10 \cdot \log(\eta_o) \quad \text{SPL} = 97.4 \text{ dB}$$